

Weight—Approx. 2.4kg



## PictureMate™ PM 210

**PRINTER TYPE**  
PRINTING METHOD  
NOZZLE CONFIGURATION  
PRINT DIRECTION

On-demand ink jet (piezoelectric)  
90 nozzles each (Black, Cyan, Magenta, Yellow)  
Bi-direction printing

**PRINT QUALITY**  
MAXIMUM RESOLUTION  
MINIMUM INK DROPLET VOLUME

5760 x 720 dpi (with Variable-Sized Droplet Technology)  
3pl

**PRINT SPEED**  
PHOTO 10 x 5cm / 4 x 6in\*1

Approx 53sec per photo\*2

**CONTROL PANEL**  
LCD SCREEN  
RESOLUTION

2.0" CSTN  
93 ppi

**PAPER HANDLING**  
PAPER FEED METHOD  
PAPER HOLD CAPACITY  
PAPER SIZE  
PRINT MARGIN

Friction feed  
Input capacity: 20 sheets for PictureMate Photo Paper (10 x 15cm / 4 x 6in)  
100 x 150mm (4 x 6")  
0mm top, left, right, bottom via custom settings in printer driver  
Otherwise 3mm top, left, right, bottom

**INK CARTRIDGES**

4-colour all in one pack T5852†

**INTERFACE**

USB 2.0 (High speed) for PC connections\*\*  
USB 2.0 (Full speed) port for PictBridge & USB Direct Print Connections

**CARD SLOT FUNCTION**  
BUILT-IN SLOT  
SUPPORTED MEMORY CARDS

4 slots: Compact Flash Type I&II, Memory Stick, SD, xD-Picture Card  
CompactFlash Type I&II, Memory Stick, MagicGate Memory Stick, Memory Stick Pro, Memory Stick Duo\*, Memory Stick Pro Duo\*, MagicGate Memory Stick Duo\*, Memory Stick Micro\*, Microdrive, SD Memory card, miniSD card\*, microSD card\*, SDHC card, mini SDHC card\*, microSDHC card\*, MMC, xD-Picture Card, xD-Picture Card Type M, xD-Picture Card Type H  
JPEG (Exif ver 2.21) - DCF version 1.0/2.0, TIFF, PRINT Image Matching, PRINT Image Matching II, DPOF Compliant  
\* Requires adapter

FILE FORMAT

**INPUT DATA BUFFER**

256KB

**COLOUR MATCHING**

sRGB, AdobeRGB

**NOISE LEVEL**

48.9dB(A) per ISO7779 4 x 6 / PGPP / EnhanceFine detail: ON Sound Power

**ELECTRICAL SPECIFICATIONS**

Rated Voltage  
Rated Frequency  
Power Consumption

AC 100 - 240V††  
50 - 60 Hz  
Continuous Printing: 10W  
Low power mode: 4.0W  
Energy star rating

†† Universal Voltage by AC adapter

Sleep Mode: 2.3W(240V)  
Power OFF : 0.3W(240V)

**PRINTER SOFTWARE ON CD-ROM**

PRINTER DRIVERS

Windows 2000 / XP / XP-64  
Mac OS 10.2.8 or later  
Yes

ON-LINE GUIDE

**OPTIONS**

Bluetooth Photo Print Adapter C12C824384

\*1 When printed on PictureMate Photo Paper with the condition of EnhanceFine detail: Off, borderless via PC.

\*\* To use USB port, your PC must conform to PC98 specifications, and have Windows preinstalled. Consult the documentation provided with your PC for further information about USB connectivity. Note also that printing errors may occur if non-standard cables or more than 2 USB hub connections are used.

† The printer ships with full cartridges and part of the ink from the first cartridges is used for priming the printer.

Printing Speed Data Pattern

The thumbnail images below show the printing patterns used to determine printing speed specifications.

System Configuration of Printing Speed  
CPU: Pentium 4, 3.2GHz  
RAM: 1GB  
I/F: USB2.0 Hi-Speed  
OS: Windows XP Home Edition  
Soft: Adobe Photoshop 7.0E



\*2  
Photo 4R  
(4"x 6")

Printing speed test results vary according to system configuration, dpi setting, and print mode setting. However, documents and photos other than those pictured above can be substituted without significantly affecting test results.



Epson is the registered trademark of Seiko Epson Corporation.

All other product names and other company names used herein are for identification purposes only and are the trademarks or registered trademarks of their respective owners.

Epson disclaims any and all rights in those marks. Scan/Print samples shown herein are simulations. Specifications are subject to change without notice.

# EPSON

EXCEED YOUR VISION

INDIA - (91) 80-305-15000, CALCUTTA - 228 31589/90,  
CHENNAI - 302 77500, MUMBAI - 282 61515/16/17,  
NEW DELHI - 306 15000  
INDONESIA - (62) 21-572-3161  
MALAYSIA - (60) 3-562-88288  
PHILIPPINES - (632) 813-6567  
SINGAPORE - (65) 6586-5500, (65) 6586-3111  
THAILAND / INDOCHINA - (662) 685-9888

Dealer's Stamp